

IMPORTANT SAFEGUARDS

When using electrical equipment, basic safety precautions should always be followed, including the following:

THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. DISCONNECT POWER TO ALL CIRCUITS BEFORE WIRING FIXTURE. INSTALL IN ACCORDANCE WITH ALL NATIONAL, STATE, AND LOCAL CODES. DO NOT CONNECT TO AN UNGROUNDED SUPPLY. READ ALL FIXTURE MARKINGS AND LABELS TO ENSURE CORRECT INSTALLATION OF FIXTURE. SUPPLEMENTAL INSTRUCTIONS MAY BE LOCATED ON THE FIXTURE, IN ADDITION TO THIS INSTRUCTION SHEET, REGARDING ORIENTATION, OR MOUNTING RESTRICTIONS.

SAVE THESE INSTRUCTIONS

1. Prepare ceiling with a rectangular cutout with 90 degree corners making sure that both top and bottom panels are cut on the same plane. Cutout size is 17.50" x 20.50" for EPMP-1722 or 24.00" x 24.00" for EPMP-2424.
4. Insert collar/trim assembly through cutout from the room side.



2. Remove luminaire base (trim and collar/trim assembly) from packing materials. (Please leave the Electrical assembly packed until step 8).
3. Remove four (4) screws that secure top base to collar. Set top base aside.
5. Support Collar/Trim assembly in place.



- Align Top Base to Collar/Trim assembly and install the ten pieces of #10-x sheet metal screws. Tighten to 14 inch pounds (hand-tight).



- Verify that the gasket is sealing the room-side surface and that there is compression of that gasket. If not, verify ceiling thickness (allowable ceiling thickness 4.00" ± 0.125").
- Remove Electrical assembly from packing materials and set on a stable surface with LEDs facing up (adjacent to fixture from above ceiling).



- Read marking labels and all package markings for important information including input voltage requirements.
- Carefully remove wire-way cover.



- Make all electrical connections from a sealed conduit fitting or bushing to prevent condensation from entering the luminaire.



- Verify grounding connections to green terminal/ wire provided.



- Secure wireway cover so that all wires are contained within the compartment.



- LEDs are sensitive and must be protected. Do not place the electrical assembly face down on any surface other than the Top-Base, as intended.

15. Align Electrical assembly with Top Base and connect green bonding jumper.



16. Secure Electrical assembly to Top Base with (4) captive screw provided.



17. Secure steel aircraft support cable(s) to Top Base and structure, removing slack in cables.
18. Energize from a protected branch circuit not exceeding the marked input voltage ratings.

CUSTOMER SERVICE

For technical assistance, call 1-800-4KENALL (1-800-453-6255). For additional instructions, go to www.kenall.com/Installs

WARRANTY

For warranty information visit www.kenall.com/Resources/Certified-Performance-Warranties



www.kenall.com | P: 800-4-Kenall | F: 262-891-9701 | 10200 55th Street Kenosha, Wisconsin 53144, USA

This product complies with the Buy American Act: manufactured in the United States with more than 50% of the component cost of US origin. It may be covered by patents found at www.kenall.com/patents. Content of specification sheets is subject to change; please consult www.kenall.com for current product details. ©2019 Kenall Mfg. Co.

A brand of  **legrand**